

# FI/CQR338

12 volt SMOKE DETECTOR



The FI/CQR338 series of detectors are ideal devices to use with 12 volt monitored panels, they can also be integrated into intelligent systems and used with security panels too. The devices also have dual LED's for 360° visibility allowing easier identification of device in fault or fire condition, and comes complete with base.

Independently certified to EN54-7

- Dual LED's for 360° visibility
- Advanced detection and discrimination algorithms
- Easy Installation and maintenance
- Sleek low-profile housing
- Durable sensor head, no need for replacement
- 4 Wire
- Comes complete with base
- NC/NO output

## FI/CQR338-4-12V Specifications

VOLTAGE	10.2 - 13.8V
PERMISSIBLE CURRENT	80 mA (max)
STANDBY CURRENT	320uA (max)
ALARM CURRENT	35mA
FREQUENCY	3 - 5 sec
START-UP TIME	60 Sec (max)
DIMENSIONS	Dia: 100mm H: 46 - 60mm
WEIGHT	130g / set with base
OPERATING TEMPERATURE	-10 to +50°C
HUMIDITY	0 to 95% RH, non-condensing or icing
PROTECTION CATEGORY	IP42
ORDERING INFORMATION	FI/CQR338-4-12V



Address: CQR Fire & Security, 125 Pasture Road, Moreton, Wirral, CH46 4TH, UK.



Contact us:

Phone:

Tel: +44(0)151 6061000

Fax: +44(0)151 6061122

Online:

Web: [www.cqr.co.uk](http://www.cqr.co.uk)

Email: [info@cqr.co.uk](mailto:info@cqr.co.uk)

